



The Seraph CX panel is a combination 2-wire and 4-wire panel. It can take standard detectors, call points, sounders and beacons, as well as accepting 2-wire sounders on the zones. You can use it in any combination of 2 or 4 wire. 4-12 Zone come with 4 sounder circuits rated at 1amp and can take up to 2 x 7Ah 12v batteries.

Special Features:

- Fire and Fault Relays
- Isolate all Functions
- One man test
- Evacuate
- Pre 1988 mode (Short circuit for fire)
- Class change input
- Sounder delay option (4-12z only)

Operating Voltage	230V AC, 50-60Hz
PSU Rating	1.5A 24Vdc
Max Battery Size	2 x 7Ah 12V
Aux Output	24Vdc 500mA
Zone Rating	1A
Fire Relays	2 x Reset on Reset, 1 x Reset on Silence
Fault Relays	1 x Fault
Inputs	1 x Non-latching Remote Evac (470 ohm trigger)
Sounder Circuits	4 x 1A
One Man Test	YES

Part no.	Concept Panels
8802F	2 Zone Conventional Panel
8804F	4 Zone Conventional Panel
8806F	6 Zone Conventional Panel
8808F	8 Zone Conventional Panel
8812F	12 Zone Conventional Panel

Part no.	Special Panels
880BL	Flush Kit (Large)
8800BGD	Glass door
8800R	12 Zone Repeater
8800RS	12 Zone Serial Repeater

